

# marantz®



## MM7025 - Stereo Main Amplifier

The MM7025 is the ideal two-channel main amplifier with a whopping 140W rms into 8 ohms per channel. Use it as an AV pre-amplifier to give your front channels an earth-moving boost or simply to make a sensational upgrade to an existing stereo system. And, because the technology is the same as that in the MM7055 and MM8003 using them in combination is fast, efficient and friendly. It's a great flexible customisation enabler. And, as with the big brother 7055, XLR inputs, DC triggers and Marantz bus.

### MAIN FEATURES

- 2ch power amplifier
- 2x 140 Watts (8 ohm) / 2x 170 Watts (6 ohm)
- Current Feedback circuitry
- High performance power supply
- XLR inputs
- DC Trigger control inputs

because music matters



SPECIFICATIONS	MM7025	SPECIFICATIONS	
<b>FEATURES</b>		Power Output (8/6 Ohm RMS)	140/170 Watts
Channels	2	Power Output (8/6 Ohm DIN)	-
Current Feedback Topology	o	Power Output (8/6 Ohm IHF)	-
Phono EQ: Standard/Current Feedback/Constant Current Feedback	-/-/-	Bridged Power Output (8 Ohm RMS)	-
HDAM version	-	Frequency Response	8Hz-100kHz
Power Transformer: Toroidal/EI	-/o	Total Harmonic Distortion	0.03%
High Grade Audio Components	o	Damping Factor	100dB
Customised Components	o	Input Sensitivity: MM	-
Symmetric PCB layout	-	Input Sensitivity: MC	-
Aluminium extrusion heatsink	o	Signal to Noise Ratio: MM/MC	-/-
Copper plated chassis	-	Input Sensitivity: High level	1.2V/22kohm
Tri-Tone Control (Bass/Mid/Treble)	-	Input Sensitivity: Balanced High level	2.4V/30kohm
Balance/Bass/Treble/Loudness	-/-/-/-	Signal to Noise Ratio: High level	105dB
<b>OTHER</b>		<b>GENERAL</b>	
Linear Drive Power Supply	o	Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/-
BTL possibility	-	Metal Front Panel	o
Bi-Amp and Multichannel option	-	Power Consumption in W	220
Shottkey diodes	-	Standby Consumption in W	0.4
Input Buffer Amp (All inputs/CD only)	o/-	Auto Power off	o
Separate solid heatsinks	-	Detachable Power Cable	o
System block shielding: copper/metal/none	-/-/-	Remote Control	-
Double layer bottom plate	-	System Remote Function	-
Source Direct	-	Maximum Dimensions (W x D x H) in mm	440x350x126
Power Amp Direct	o	Weight in kg	10.5
Standby mode	o		
<b>INPUTS/OUTPUTS</b>			
Phono Input: MM/MC	-/-		
Balanced In/Out	2/-		
Pre-Out/Main In	-/2		
Power Amp Direct In	o		
Gold Plated Chinch	-		
Speaker A/B	-		
Speaker terminal: Screw/Marantz/WBT	o/-/-		
Number of terminals	2		
Marantz remote bus	o		
Remote power control (Trigger In/Out)	o		
Flasher In/IR receiver In	o/-		
Headphone Out	-		

www.marantz.com

# because music matters