



POWER BOX DS2 Sources

Universal linear power supply for up to 5 components & 1 turntable

MSRP 549 € (incl. VAT)

colour options:



real wood side panels:



- Purest & cleanest power using non-switching power supply
- 5 Box Design component & 1 turntable power output
- Not suitable for integrated & power amplifiers, receivers etc
- Soft start system avoids current inrush in primary winding
- Audio type toroidal transformer
- Main isolating transformer with copper foil shielding
- Secondary voltage rectification with precise regulation
- High filtration capacity (10.000 μ F)
- Low ESR capacitors
- Low noise components with surge protection
- Colour options: silver and black, with optional wooden sidepanels (rosenut, walnut, eucalyptus)

Input voltage: AC 230V/50Hz IEC C15 connector
(120V/60Hz US)

Output voltage/current (standard cables included): 2 x 9V / 2A max (1.8mm connector); 3 x 18V / 1A max (2.5mm connector); 1 x 15V / DC-turntable (2.1mm connector)

*High-End power cables **Connect it Power DS** optionally available

CAUTION: Do not use for other voltages!

Filtration capacity: 10.000 μ F

Output voltage ripple: < 1mV

Dimensions W x H x D: 203 x 72 x 207mm (aluminium)
240 x 72 x 209mm (wood)

Weight: 3000g (aluminium), 3400g (wood)

Power Box DS2 Sources: Cleanest power for ultimate sound of Box Design components plus turntable!

It is a proven fact that a power supply is a very important part of the audio path and significantly contributes to the sonic quality of an audio product. In order to offer the possibility of improving sound quality, we designed our linear power supply Power Box DS Sources. It significantly enhances the sound quality of up to six Box Design components, like streamers, CD players, pre-amplifiers and also offers the possibility to connect a DC-driven turntable.

A linear power supply consists of a massive toroidal transformer with shielding between primary and secondary winding, which acts as an isolating transformer and avoids penetration of interferences from mains into the audio component. The built-in transformer has a much higher power reserve compared to the standard power adapter. It has very low output impedance and in combination with large filtration capability it can easily manage all power needs. Sound staging, darkness of silent backgrounds and small detail resolution will improve

strongly and contribute to a far better overall performance of each component.

Six standard connection cables are included in delivery. Special highend super shielded connection cables in these lengths are available on request: 20cm, 40cm, 80cm, 1m.

The following interconnect power cables are supplied in box:

2 x 9V (1.3mm connector)

3 x 18V (2.5mm connector)

1 x 15V (2.1mm connector) – to connect a DC driven Pro-Ject Audio Systems turntable.*

*ATTENTION: NOT SUITABLE for the following turntables: Xtension 9, Xtension 10, Xtension 12, RPM 9, RPM 10 and the models of Signature line, with high power consumption and a heavy, mass loaded, platter. For these turntables we recommend the **Power Box RS Uni 1-way** with the 15V turntable modification. For more information please contact your dealer.

Higher end power cables **Connect-it Power DS** with su-



rosenut side-panels



walnut side-panels



eucalyptus side-panels

Compatible with:

9V products:

CD Box DC
CD Box DS2 T
CD Box S
CD Box S2
Dock Box S Digital
MaiA CD
Media Box S
Remote Box S
Stream Box DS
Stream Box DS net
Bluetooth Box E
Bluetooth Box S
DAC Box S FL
DAC Box S USB
Switch Box S
Tuner Box S
USB Box S+

15V turntables:

all DC driven 15V Pro-Ject turntables

***ATTENTION: NOT SUITABLE** for the following turntables: Xtension 9, Xtension 10, Xtension 12, RPM 9, RPM 10 and the models of Signature line, with high power consumption and a heavy, mass loaded, platter. For these turntables we recommend the **Power Box RS Uni 1-way** with the 15V turntable modification. For more information please contact your dealer.

18V products:

A/D Phono Box S
AD Box S2 Phono
DAC Box DS
DAC Box E
Dock Box S Fi
Head Box DS
Head Box S
Head Box S USB
Optical Box E Phono
Phono Box
Phono Box DS
Phono Box DS+
Phono Box DS2
Phono Box DS2 USB
Phono Box E
Phono Box E BT
Phono Box MM
Phono Box S
Phono Box S2
Phono Box S2 Ultra

Phono Box ultra 500
Phono Box USB
Phono Box USB V
Pre Box S
Pre Box DS
Pre Box DS2 Analogue
Record Box E
Record Box USB
Speed Box S
Speed Box S2
CD Box DS
DAC Box DS2 Ultra
Head Box DS2 B
MaiA pre
Pre Box DS2 Digital
Speed Box DS
Stream Box DS+
Tube Box DS
Tube Box Ds2
Tube Box S
Tube Box S2

