

STAX®



SRS-X1000 | Earspeaker (SR-X1) + Amplifier (SRM-270s) A Premier Electrostatic Earspeaker System

The Ultimate Entry into Electrostatic Sound

Designed for audiophiles eager to delve into the world of electrostatic earspeakers without compromise, the SRS-X1000 stands as a beacon of innovation and quality. As the successor to our long-standing SRS-3100 electrostatic audio system, it pairs the brand new SR-X1 earspeakers with the newly developed SRM-270S driver unit, setting a new benchmark for entry-level electrostatic audio system.

SR-X1 Earspeakers: Offering a pure and immersive sound experience with:

- **Wide Frequency Response:** Ranging from DC to 35,000Hz for full-spectrum audio reproduction.
- **Minimal Distortion:** Harmonic distortion of 0.01% or less ensures crystal-clear sound.
- **Heritage Design:** Embodying the spirit and concept from the SR-1 and SR-X earspeakers.

SR-X1 (Earspeaker)

- **Type :** Push-pull electrostatic circular speaker, rear-opening enclosure
- **Unit Shape :** Medium-sized circular
- **Fixed electrodes:** High-precision etched electrodes
- **Playback frequency range:** 7-41,000Hz
- **Capacitance:** 110pF (including attached cable)
- **Impedance:** 145kΩ (at 10kHz/including 2.5m attached cable)
- **Sound pressure sensitivity:** 101dB/100Vr.m.s. input/1kHz
- **Bias voltage:** 580V DC
- **Cable conductor:** OFC
- **Cable shape :** Parallel 6-core, wide low capacitance cable, 2.5m
- **Earpads:** Genuine sheepskin leather (skin contact area), artificial leather (attachment area)
- **Weight:** 234g (main unit only)

SRM-270S Driver Unit: The heart of the SRS-X1000, featuring:

- **Enhanced Heat Dissipation:** A 3mm-thick front aluminum panel and a larger aluminium extrusion case for effective heat management.
- **High-Grade Connectivity:** RCA pin jacks and a 3mm-thick front aluminum panel ensure a pristine connection.
- **Low Noise FET:** Selected for the First Stage amplifier, paired with a refined emitter follower circuit in the Output Stage for unparalleled clarity.
- **Compact Chassis:** Easy for placement, transportability and aesthetic appeal.
- **Flexible Installation:** PARALLEL OUT terminals facilitate easy incorporation into your existing audio system, whether for music enjoyment or enhancing movie experiences at your desktop or bedside.

SRM-270S (Driver unit)

- **Frequency response:** DC to 35,000Hz/+0, -3dB
- **Harmonic distortion:** 0.01% or less/1kHz 100V r.m.s.
- **Amplification:** 58dB (800 times)
- **Rated input level:** 125mV/100V r.m.s. output
- **Maximum output voltage:** 280V r.m.s./1kHz
- **Input impedance:** 25kΩ
- **Input terminals:** RCA x 1
- **Output terminal:** Parallel out x 1
- **Bias voltage:** 580V DC
- **Power supply voltage:** 100V AC adapter included
- **Power consumption:** 12VDC/500mA
- **External dimensions:** 132(W)×38(H)×153(D)mm (excluding protruding parts)
- **Weight:** 540g

Your Gateway to Unprecedented Sound

The SRS-X1000 embodies a perfect fusion of tradition and innovation, offering an accessible yet uncompromised entry into the elite world of electrostatic earspeaker audio systems. Whether you're a long-time audiophile or exploring high-fidelity sound for the first time, the SRS-X1000 provides an unparalleled listening experience.